GP-626, High Performance, GPS PCI Express Half-Mini Card w/ I-PEX RF Connector

Overview

GP-626 is equipped with the **u-blox 6** high-sensitivity engine, RF connector, and optional backup battery. The Mini PCI Express standard design allows it to be easily applied in devices with PC architecture. The half-length design allows it to be used in dimension demanding environment. In addition to standard USB interface, it also supports optional UART/TTL interface.

The backup battery allows faster position fix and it is optional in case extended temperature range is required.

Our experienced design provides not only excellent GPS performance but also quality and delivery assurance.

Applications

- Industry PC
- Notebook PC / Netbook PC / Tablet PC
- School Bus / Transit / Police / Fleet

Features

- PCI Express Mini Card standard compliant
- Built-in RF connector, reduce RF tuning efforts
- The tiny I-PEX RF connector allows flexibly placing GPS antenna at a suitable location.
- External active antenna short circuit protection
- Optional backup battery for faster position fix.
- Support USB or UART/TTL interface.
- In addition to default u-blox USB driver, optional
 Prolific USB driver is also available by request.
- High sensitivity*:-161dBm tracking/-147dBm





acquisition

- Up to 5Hz update rate (default 1Hz)
- OMA SUPL compliant A-GPS support
- SBAS (WAAS, EGNOS, MSAS, GAGAN) support
- Windows location sensor support
- Excellent EMI protection

Technical Specifications

Receiver Performance Data*

Receiver Type	50-channel,		
	L1 frequency, C/A code		
Horizontal Position Accuracy	< 2.5m (Autonomous) < 2.0m (WAAS) (CEP, 50%, 24-hour static, -130dBm, SEP < 3.5m)		
Velocity Accuracy	<0.1 m/s (speed) <0.5° (heading) (50% @ 30 m/s)		
Time Pulse Signal Accuracy	30ns (RMS) <60ns (99%)		
Time To First Fix Hot start Warm start Cold start	Autonomous (All at -130dBm) 1sec 27sec 27sec		
Sensitivity (Autonomous)	-147dBm (acquisition) -161 dBm (tracking & navigation)		
Max. Update Rate	5Hz		
Max. Altitude	50,000 m		
Max. Velocity	500 m/s		

ADH Technology - Your Location Partner

Protocol Support	NMEA 0183 v2.3(compatible to 3.0)
	UART: 4800, 9600, 38400 bps N,8,1;
	GGA, GLL, GSA, GSV, RMC, VTG, TXT
SBAS Support	WAAS, EGNOS, MSAS, GAGAN
Dynamics	< 4g

^{*} Note. According to IC Spec

Electrical Data

Power Supply	3.3 ± 0.3 V
Power Consumption	56 mA / average tracking
USB I/O (V)	V _{IH} : 2 ~ 3.3, V _{IL} : 0 ~ 0.8
	V _{OH} : >= 2.8, V _{OL} <= 0.3

Environmental Data

Operating temperature	-40 ~ 85°C w/o battery
	-20~60°C w/ battery
Storage temperature	-40 ~ 85°C w/o battery
	-40~60°C w/ battery

Mechanical Data - 30 x 26.8 x 2.8 (mm)




52-Pin definition

Name	PINs	Function	I/O
vcc	2,24,39,41,52	3.3V power supply, Min 3.0V, Max 3.6V	Input
GND	4,9,15,18,21,26, 27,29,34,35,37, 40,43,50	Ground	Input
USB_DM	36	USB data signal minus	1/0
USB DP	38	USB data signal plus	1/0
LED	42	GPS fix indication	Output
nRESET	5	RESET pin	Input
RXD'	45	TTL input into GPS	Input
TXD!	47	TTL output from GPS	Output
NC	Remaining pins	No connection	-

TTL model only, NC for USB model

GPS PCI Express Half-Mini Card/ GP-626



Application

 Mount GP-626 on main board, connect I-PEX to GPS active antenna.

Ordering Information GP -626X[&]

TTL 4800bps, N-8-1
GGA, GSA, GSV, RMC, VTG, TXT
TTL 9600bps, N-8-1
GGA, GLL, GSA, GSV, RMC, VTG, TXT
u-blox USB
GGA, GLL, GSA, GSV, RMC, VTG, TXT
Prolific USB, 9600bps, N-8-1
GGA, GLL, GSA, GSV, RMC, VTG, TXT

[&]amp;Default with battery.

Proprietary; reserved pins of PCle Mini Rev. 1.2 are used

^{*}This document is subject to change without notice.